Page 1/2

For full specifications and programming features it is essential to refer to the TVTEL Programming Manual available free at: www.telephoneentry.co.uk

(1) Download of TVTEL software program for installation on your PC, includes pdf of manual. (2) Download pdf of manual only from Installation Guides section.

Description	TVTEL 2K	TVTEL 240	TVTEL PB	TVTEL LP	Comparisons / Comments
Material (Brass to special order)	BS316 S.Steel	BS316 S.Steel	BS316 S.Steel	BS316 S.Steel	
Display	80mm x 80mm lexan digital display	Not required	Not required	Not required	
Capacity	1 - 2000 way	1 - 240 way	1 - 14 way	1 - 3 way	
Telephone numbers per Resident (CB = Call-Button)	Scroll Display = 2nº Speed Dial = 2nº CB 1 - 6 = 2nº each	Speed Dial = $2n^{\circ}$ CB 1 - 4 = $2n^{\circ}$ each	Call-Button 1= 4n° CB 2 - 14 = 2n° each	CB 1 - 3 = 4nº each	
Resident / Building / Block / Business names feature on panel display	Yes	No	No	No	
Scroll facility	Yes	n/a	n/a	n/a	
Speed dial	Yes	Yes	n/a	n/a	
Call-Buttons (CB)	Max 6nº in addition to Scroll Display	Max 4n° in addition to Speed Dial	Max 14n° can be expanded to 64 call-buttons.	Max 3n°	
Resident can have more than 1 entry	Yes	Yes	n/a	n/a	
Keypad codes	2000	1024	No	No	
Keypad code length	3 - 8 digits	3 - 6 digits	n/a	n/a	
Keypad codes can be date, day, time controlled	Yes	Yes	n/a	n/a	
Keypad blocked feature	Yes	No	n/a	n/a	
Protections	Please note TVTEL 2K possibili	Please note TVTEL 2K possibilities far more comprehensive than other models.	n other models.		
Friends & Family only	Yes	Yes	No	No	
Hidden	Yes	Yes	No	No	
Anti-Nuisance Calls	Yes	Yes	Yes	No	
Social Hours only	Yes	Yes	Yes	No	
Programming (Remote modification of <u>all parameters</u> / data as standard)	PC with modem	PC with modem or via telephone	PC with modem or via telephone	Via telephone	
Back-Up & Restore feature	Yes	Yes	Yes	No	
Copy feature for sites with multiple panels (Enter the information once, then copy to other panels)	Yes	Yes	Yes	No	
Database facility	Yes	Yes	Yes	No	
Call Log history	Yes	No	No	No	



For full specifications and programming features it is essential to refer to the TVTEL Programming Manual available free at: www.telephoneentry.co.uk

(1) Download of TVTEL software program for installation on your PC, includes pdf of manual. (2) Download pdf of manual only from Installation Guides section.

Description	TVTEL 2K	TVTEL 240	TVTEL PB	TVTEL LP	Comparisons / Comments
Printout facility to create Administration Folder ie Residents and telephone numbers, settings etc.	Yes	Yes	Yes	No	
Call Progress Reassurance for Visitor	Yes	Yes	Yes	Yes	
Audio information messages at panel for visitor	Yes	Yes	Yes	No	
Customer can customise audio messages	Yes	Yes	Yes	n/a	
"Call from Door Panel" announcement to person answering call from panel	Yes	Yes	Yes	Sends unique ID number	
Customise announcement to person answering call "Call from Gate", "Call from Rear Door" etc.	Yes	Yes	Yes	See above	
Panel displays date and time	Yes	No	ON	No	
Visual information messages for visitors at panel (not just flat n°)	Yes	No	oN	No	
Customer can customise visual messages	Yes	n/a	n/a	n/a	
Tradesman button that is date, day, time controlled	Yes	Option	Option	Option	
Tradesman keypad codes that are date, day, time controlled	Yes	Yes	No	No	
Selection from Date, Day, Time profiles	5 n°	Option, 1n°	Option, 1n°	No	
Automatic summer / winter time correction	Yes	No	No	No	
Global prefix feature	Yes, 1 - 4 digits	Yes, 1 - 4 digits	Yes, 1 - 4 digits	Yes, 1 - 4 digits	
Relays	2n° (+ 5V output trigger) = 3n°	2nº	2nº	ln°	
Latch relay n° 1 command from handset	Yes	Yes	Yes	No	
Non-Volatile memory	Yes	Yes	Yes	Yes	
Power Requirement	12vdc regulated	12vdc regulated	12vdc regulated	Line powered	