



PROXIMITY vandal proof reader

For use with Switch2 or Net2

A great solution for vulnerable areas

The reader is buried in a wall or door frame

Supplied with a range of coloured caps

Innovative design

IP67 rated - suitable for external use

About

The vandal proof reader is for use with Switch2 and Net2 systems. The barrel-like construction of the reader means that it can be buried in a wall. This means that it is ideal for use in vandal prone areas where malicious damage could be a problem. Black and white caps are supplied with the reader. The end cap is used as a marker, so users know where to present their tokens. Other colours are available.

Installation

The reader is wired as shown on the control unit label. The reader itself is inserted into a 20mm diameter hole in the wall or door frame. The cap is then mounted as a visual marker for users. The reader should not be mounted into metal. The illustration below shows the different fitting options.

Web links

| | |
|---|---------------------------|
| http://paxton.info/97 | Specifications |
| http://paxton.info/76 | Installation instructions |
| http://paxton.info/77 | 3D visual |

Operation

A token is read by holding it within close proximity of the reader. Once a token has been read the control unit looks up the access permissions of that user. Access is then granted or denied as appropriate.



| Sales code | Description | Retail price |
|------------|-------------------------------|--------------|
| 568-855 | PROXIMITY vandal proof reader | £135.00 |