

SCANTRONIC 9651EN-00

The Scantronic 9651EN-00 is a fully programmable, 8 zone security alarm panel designed to conform to PD6662:2004 Grade 2X system requirements.



PD 6662 : 2004 GRADE 2X SECURITY SYSTEM

The 9651EN-00 is ideally suited to both home and small commercial security applications, combining maximum flexibility with ease of use to provide optimum security when and where you need it. Simple A, B, C and D setting buttons let you split the system into four areas, enabling you to set the whole, or just parts of the alarm protection.

Up to 4 attractive remote keypads can be added to any system. The 9930 keypad supplied (as pictured above) uses a 4 or 6-digit PIN code to control system operation. To further simplify operation and minimise the chance of operator error you have the option of using a personal-encrypted, key-ring proximity tag. Alternatively, the optional-extra 9940 keypad has this facility built-in as standard. (see right)

A 9651 EN-00 panel can be connected to any speech dialler or plug-by digital communicator via its integral communications output socket. Its three fully programmable outputs further enhance system flexibility.

A 700 event log, fully date and time stamped to comply with the Association of British Insurers requirements, provides a complete record of system operation and service information.



Optional 9940 Keypad



SCANTRONIC 9651EN-00

TECHNICAL SPECIFICATION

PD6662:2004 Compliance*	Grade 2X, Environmental Class II
Zones	8 fully programmable (CC, with global tamper on panel, or 2 Wire FSL)
Zone Attributes	Each zone can be programmed as one of the following types – personal attack, fire, normal alarm, final exit, 24 hour, entry route, 'not used' shock analyser (zone 1-4 only) technical alarm, key-switch, keybox, smoke detector, anti-mask, Forbikobler, AC fail, low battery, battery fault, power output fault, fault. The following attributes are also available:- chime, soak test, double knock, omit allowed, anti-mask.
Panel	9651EN-00 blank end-station control panel and 9930 LCD keypad as a kit
Keypads	Accepts up to 4 x 9930 or 9940 remote keypads (or any combination)
Proximity Reader	9930 keypad requires an additional 934EUR-50 Scanprox plug-on reader kit. 9940 keypad includes a proximity reader as standard.
Keypad Display	Full feature, plain text, LCD display, 2 x lines, 16 characters per line
Level Setting	A = Full set. B, C, and D offer part set options
Event Log	700 event log with date and time stamped, viewed or downloaded
Keyswitch	Keyswitch zone type, full = A, part = B setting/unsetting, disarm and reset.
Codes	50 x 4 digit user access codes and/or 49 proximity tags, 1 engineer code
Internal Sounder	Accepts up to 2 x 16 ohm internal sounders, exit/entry tones via internal sounder with electronic volume control
Outputs	3 open collector output programmable as bell, exit/entry follow, armed lamp, set latch, shock reset, walk test (LED enable), ready lamp, 24 hour alarm, strobe, smoke reset, strobe when setting, siren test, pulsed set, pulsed unset, set complete, unset complete, system alarm, fire, PA, set fail, general fault, all fault
Power Supply	Conforms to EN50131-6 Type A power supply, rated power output 580mA
Battery	Stand by battery 12 volt, 7Ah rechargeable lead acid, gel type
Dimensions	Control panel (H x W x D): 240 x 240 x 90mm, 9930 keypad: 120 x 170 x 27mm, 9940 keypad: 115 x 115 x 25mm,
Weight	Control panel = 3.3 kg 9930 keypad = 260gm 9940 keypad = 205gm
Temperature Range	Environmental Class II -10C to 55C @ 75% RH
Secondary Communications Outputs	Any wire-in secondary communication device via 8 fully programmable outputs

Installer Details :

* For non - PD6662: 2004 UK installations model no. 9651 UK-00 is available. Export versions are also available.

For information on your local stockist contact our Marketing Department

telephone: 0870 7575 400 fax: 01594 545 445
email: marketing@coopersecurity.co.uk

Cooper Security, Security House, Vantage Point Business Village, Mitcheldean, Gloucestershire, GL17 0SZ. UK

www.coopersecurity.co.uk

Scantronic is a leading brand of Cooper Security Ltd, part of Cooper Industries, which employs over 28,000 people at more than 100 manufacturing sites around the world.

www.scantronic.co.uk



another product from:

COOPER Security